

CROMMELINS GENERATOR 3.8KW YANMAR DIESEL MINESPEC



SPECIFICATIONS

MODEL NUMBER	CG40YDEM
Max. Watts (w)	3800w
Cont. Output (w)	3500w
Starting System	Electric Start
Phase	Single
Fuel Type	Diesel
10amp outlet s/phase	2x 10Amp
Alternator	Sincro
Voltage (V)	240v - 50hz
Engine Power/Model	6.7HP L70
Engine Brand	Yanmar
Fuel Tank (L)	3.3L
Noise Level (dB @ 7m)	
Weight (kg)	120kg
Dimensions (LxWxH)	755 x 510 x 550mm
Package (LxWxH)	980 x 530 x 660mm
Manufacturers Warranty	2 Years
Barcode	

Electric start, Yanmar engine, diesel generator.

This Crommelins generator diesel 3.8kW (max.) output is electric start for easy starting and comes with mine-spec. It will suit small to medium jobs powering tools and equipment and is site safe*. It is ideal for mine sites, hire and construction.

Electric start allows an operator the simplicity of turning a key to start the generator. Mine-spec includes hire-pack (IP66 weatherproof outlets with RCD protection, two wheels, lifting bar/hook, fold-out transport handles) as well as fire extinguisher, battery isolator, bunding and emergency safety stop.

It features a reliable diesel Yanmar engine, Sincro brushless alternator all built into a 32mm Australian fabricated heavy-duty steel frame. Assembled and tested in our Australian factory.

A hard-working, long life generator and built to work in rough conditions it also has a two-year manufacturer's warranty. Customization options include; long-range fuel tank, Anderson jump plugs, recoil start lock and also fleet coloured

www.crommelins.com.au



IDEAL FOR

- ▶ Hire and Rental
- ▶ Mining and Oil

INDUSTRY

- ▶ Hire and Rental
- ▶ Construction
- ▶ Building
- ▶ Mining

Authorized Dealer

